Sales: 408-778-9952 | General: 408-778-4200 | Fax: 408-778-4300
Sales & Customer Support: sales@markimicrowave.com
Tech Support: support@markimicrowave.com


MM1-0626HBH

GaAs MMIC 6-26.5 GHz Double Balanced Mixer

DEVICE OVERVIEW

General Description

The MM1-0626H is a passive double balanced MMIC mixer. It delivers excellent 8 dB conversion loss, superior isolations and spurious performance across a broad 6 to 26.5 GHz RF/LO bandwidth. The LO drive requirement allows operation at as low as +12 dBm inputs. The MM1-0626H is available both as a wire bondable chip or in a 2.92mm connectorized BH package. If higher LO power is available, the MM1-0626S is recommended for higher mixer linearity.




Features

- RF/LO Bandwidth, 6 to 26.5 GHz
- IF Bandwidth, DC to 8 GHz
- LO Drive Requirement, +12 dBm Minimum
- High Performance BH Package
- CAD Optimized for Superior Isolation and Spurious Response
- Excellent Unit-to-Unit Repeatability

Applications

- SATCOM
- Test and Measurement Equipment
- Aerospace and Defense
- Electronic Warfare

Functional Block Diagram



Part Ordering Options

Part Number	Description	Package	Connectors	Green Status	Product Lifecycle	Export Classification
MM1-0626HBH	GaAs MMIC 6-26.5 GHz Double Balanced Mixer	BH	-	REACH RoHS	Released	EAR99

Rev: - | Copyright © 2026 Marki Microwave LLC.

Table Of Contents

- **Device Overview**
  - General Description
  - Features
  - Applications
  - Functional Block Diagram
- **Port Configuration and Functions**
  - Port Diagram
  - Port Functions
- **Revision History**
- **Specifications**
  - Absolute Maximum Ratings
  - Package Information
  - Recommended Operating Conditions
  - Electrical Specifications
  - Typical Performance Plots
  - Typical Performance Plots: IP3
  - Typical Performance Plots: LO Harmonic Isolation
  - Spur Tables
- **Operation**
  - Application Circuit
  - Application Circuit Description
- **Mechanical Data**
  - Outline Drawing


Revision History

Revision Code	Revision Date	Comment
-	2026-11-10	Initial Release

Rev: - | Copyright © 2026 Marki Microwave LLC.




Port Configuration and Functions

Port Diagram






Port Functions

Configuration A

Port	Function	Connector Type	Description	DC Equivalent Circuit
Port 1	LO	2.92F	Port 1 is DC short and AC matched to 50 Ω from 6 to 26.5 GHz. Blocking capacitor is optional.	
Port 2	IF	2.92F	Port 2 is DC coupled to the diodes. Blocking capacitor is optional.	
Port 3	RF	2.92F	Port 3 is DC short and AC matched to 50 Ω from 6 to 26.5 GHz. Blocking capacitor is optional.	

Rev: - | Copyright © 2026 Marki Microwave LLC.

Configuration B

Port	Function	Connector Type	Description	DC Equivalent Circuit
Port 1	RF	2.92F	Port 1 is DC short and AC matched to 50 Ω from 6 to 26.5 GHz. Blocking capacitor is optional.	
Port 2	IF	2.92F	Port 2 is DC coupled to the diodes. Blocking capacitor is optional.	
Port 3	LO	2.92F	Port 3 is DC short and AC matched to 50 Ω from 6 to 26.5 GHz. Blocking capacitor is optional.	

Rev: - | Copyright © 2026 Marki Microwave LLC.

Specifications

Absolute Maximum Ratings

Parameter	Maximum Rating	Unit
Maximum Operating Temperature	100	°C
Maximum Storage Temperature	125	°C
Minimum Operating Temperature	-55	°C
Minimum Storage Temperature	-65	°C
Port 1 DC Current	30	mA
Port 2 DC Current	30	mA
Port 3 DC Current	30	mA

Package Information

Parameter	Details	Rating
ESD	250 to < 500 Volts	HBM Class 1A
Weight	Package name: BH	12g
Dimensions	-	29.01 x 19.84 mm

Recommended Operating Conditions

Parameter	Min	Nominal	Max	Unit
LO Input Power	12	18	21	dBm

Rev: - | Copyright © 2026 Marki Microwave LLC.

Electrical Specifications


The electrical specifications apply at TA=+25°C in a 50Ω system. Typical data shown is for the connectorized BH package mixer used in the forward direction with a sine wave LO of +12 dBm and RF input power of -10 dBm, aside from linearity measurements. Min and Max limits apply only to our connectorized units and are guaranteed at TA=+25°C.


Parameter	Port Configuration	Test Conditions	Min	Typ	Max	Unit
RF Frequency Range	-	-	6	-	26.5	GHz
LO Frequency Range	-	-	6	-	26.5	GHz
IF Frequency Range	-	-	0	-	8	GHz
Conversion Loss [1]	A	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	8	-	dB
Conversion Loss [2]	B	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	9	-	dB
LO-RF Isolation	-	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	50	-	dB
LO-IF Isolation	-	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	35	-	dB
RF-IF Isolation	-	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	35	-	dB
Input IP3	A	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm Tone Spacing=1MHz Tone Power=-5dBm	-	20	-	dBm
Input IP3	B	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm Tone Spacing=1MHz Tone Power=-5dBm	-	21	-	dBm
Input P1dB	A	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	9	-	dBm
Input P1dB	B	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	9	-	dBm
Noise Figure [3]	B	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	9	-	dB
Noise Figure [4]	A	RF/LO=6-26.5GHz IF=91MHz LO Drive=+18dBm	-	8	-	dB


[1][2] Measured as a down converter to a fixed 91MHz IF.
[3][4] Mixer Noise Figure typically measures within 0.5 dB of conversion loss for IF frequencies greater than 5 MHz.


Rev: - | Copyright © 2026 Marki Microwave LLC.


Typical Performance Plots






















Rev: - | Copyright © 2026 Marki Microwave LLC.















Rev: - | Copyright © 2026 Marki Microwave LLC.


Typical Performance Plots: IP3


















Rev: - | Copyright © 2026 Marki Microwave LLC.


Typical Performance Plots: LO Harmonic Isolation














Rev: - | Copyright © 2026 Marki Microwave LLC.

Spur Table

Typical Downconversion Spurious Suppression

Typical spurious data is provided by selecting RF and LO frequencies (± m*LO ± n*RF) within the RF/LO bands, to create a spurious output within the IF band. The mixer is swept across the full spurious band and the mean is calculated. The numbers shown in the table below are for a -10 dBm RF input. Spurious suppression is scaled for different RF power levels by (n-1), where "n" is the RF spur order. For example, the 2RF x 2LO spur is 81 dBc for a -10 dBm input, so a -20 dBm RF input creates a spur that is (2-1) x (-10 dB) lower, or 91 dBc.

Typical Downconversion Spurious Suppression (dBc): Configuration A (Configuration B), Sine Wave LO

-10 dBm RF Input	0xLO	1xLO	2xLO	3xLO	4xLO	5xLO
1xRF	-27 (-23)	Reference	-34 (-35)	-27 (-21)	-50 (-45)	-54 (-47)
2xRF	-76 (-75)	-79 (-58)	-81 (-78)	-75 (-71)	-77 (-79)	-72 (-73)
3xRF	-84 (-83)	-84 (-80)	-92 (-92)	-90 (-90)	-92 (-94)	-87 (-87)
4xRF	-96 (-92)	-100 (-99)	-101 (-99)	-103 (-101)	-102 (-101)	-101 (-100)
5xRF	-102 (-100)	-110 (-107)	-113 (-112)	-112 (-109)	-114 (-111)	-112 (-111)

Rev: - | Copyright © 2026 Marki Microwave LLC.

Typical Upconversion Spurious Suppression


Typical spurious data is taken by mixing an input within the IF band, with LO frequencies (± m*LO ± n*IF), to create a spurious output within the RF output band. The mixer is swept across the full spurious output band and the mean is calculated. The numbers shown in the table below are for a -10 dBm IF input. Spurious suppression is scaled for different IF input power levels by (n-1), where "n" is the IF spur order. For example, the 2IFx1LO spur is typically 79 dBc for a -10 dBm input with a sine-wave LO, so a -20 dBm IF input creates a spur that is (2-1) x (-10 dB) lower, or 89 dBc.

Typical Upconversion Spurious Suppression (dBc): Configuration A (Configuration B), Sine Wave LO


-10 dBm IF Input	0xLO	1xLO	2xLO	3xLO	4xLO	5xLO
1xIF	-45 (-33)	Reference	-28 (-31)	-17 (-14)	-34 (-35)	-45 (-44)
2xIF	-74 (-79)	-79 (-77)	-68 (-65)	-73 (-74)	-71 (-69)	-77 (-74)
3xIF	-91 (-91)	-89 (-91)	-87 (-86)	-80 (-78)	-82 (-84)	-83 (-79)
4xIF	-104 (-102)	-105 (-104)	-101 (-102)	-102 (-101)	-100 (-102)	-102 (-101)
5xIF	-110 (-109)	-115 (-115)	-115 (-112)	-111 (-109)	-111 (-112)	-111 (-109)

Rev: - | Copyright © 2026 Marki Microwave LLC.

Application Circuit



Configuration A



Configuration B

Rev: - | Copyright © 2026 Marki Microwave LLC.

Application Circuit Description


Configuration A/B refer to the same part number (MM1-0626H) used in one of two different ways for optimal spurious performance. For the lowest conversion loss, use the mixer in Configuration A (port 1 as the LO input, port 3 as the RF input or output). If you need to use a lower LO drive, use the mixer in Configuration B (port 1 as the RF input or output, port 3 as the LO input). For optimal spurious suppression, experimentation or simulation is required to choose between Configuration A and B.

Rev: - | Copyright © 2026 Marki Microwave LLC.

Mechanical Data

Outline Drawing

Download : Outline 2D Drawing



Rev: - | Copyright © 2026 Marki Microwave LLC.

DISCLAIMER

MARKI MICROWAVE, LLC., (“MARKI”) PROVIDES TECHNICAL SPECIFICATIONS AND DATA (INCLUDING DATASHEETS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, AND OTHER INFORMATION AND RESOURCES “AS IS” AND WITH ALL FAULTS. MARKI DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT.

These resources are intended for developers skilled in the art designing with Marki products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards and other requirements. Marki makes no guarantee regarding the suitability of its products for any particular purpose, nor does Marki assume any liability whatsoever arising out of your use or application of any Marki product.

Marki grants you permission to use these resources only for development of an application that uses Marki products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Marki intellectual property or to any third-party intellectual property. Marki reserves the right to make changes to the product(s) or information contained herein without notice.

MARKI MICROWAVE, M wave logo, FastSwitch, and T3 MIXER are trademarks or registered trademarks of Marki Microwave, LLC. All other trademarks used are the property of their respective owners.

© 2026, Marki Microwave, LLC